

AUTO CHARGE 20/20

AUTOMATIC BATTERY CHARGER



Features

- 40A total: 20A battery charger, 20A battery saver
- Automatic operation regulates output to a single battery bank
- Separate 20 Amp ATC fuse protected "Battery Saver" output eliminates drain on vehicle battery when in station
- Clean output poses no interference with radios and other mobile devices
- Front ammeter indicators
- Dual cooling fans
- Automatic current limit
- Reverse polarity protected
- AC input circuit breaker protection



Specifications:

Input Voltage (Volts AC): 120

Input Current (Amp AC): 8.5

Input Frequency (Hz): 50/60 Hz

Charger Output Voltage (Volts DC): 12

Charger Output Current (Amps DC): 20

Battery Saver Output Voltage (Volts DC): 14.0

Battery Saver Output Current (Amps DC): 20

Output Fuse (Recommended): 30 Amps

Weight (lbs.): 13

Warranty: 3 Years



Part Number	Description	Electrical Data				Dimensions			Wt.
		DC Volts	DC Amps	AC Volts	AC Amps	L	W	D	
091-216-20/20	Auto Charge 20/20	12	20 / 20	120	8.5	13.125"	8.250"	5.233"	13